



kramer

3232SR-XL

32x32 Analog Balanced Stereo Audio Matrix Switcher with Redundant Power

| Ethernet - RJ-45



The Lassen XL Series offers flexibility and adaptability to any application where saving space and costs are important. 3232SR-XL is a 32x32 analog balanced stereo audio matrix switcher with redundant power, available in a compact 4RU frame. It offers control via the front panel or remotely via RS-232 or Ethernet

TECHNICAL SPECIFICATIONS

Inputs	32 Balanced/Unbalanced Stereo Analog Audio: 5-pin terminal block connectors
Outputs	32 Balanced/Unbalanced Stereo Analog Audio: 5-pin terminal block connectors
Ports	2 Sync: On BNC connectors 1 Ethernet: On an RJ-45 connector 1 RS-232/422: On a 9-pin D-sub connector 2 RS-485: On male mini-XLR connectors, for control panel 1 AC Power: On an AC power connector
Analog Audio	Input - Max. Source Level +24dBu Input - Impedance $>20k\Omega$ Output - Max. Source Level +24dBu balanced +18dBu unbalanced Output - Impedance $<50\Omega$
Enclosure	Size: 19" — 4U — mounts in a standard 19" rack Dimensions: 19" x 18.5" x 7" W, D, H